WIZ Constant Voltage Wireless LED Dimming Power Supply

Model No: LYH-200-24WB5

Profile

- •200W constant voltage WIFI&BLE wire less LED Dimming power supply
- •LED lamp belt with dimming power supply control the high power lamp belt with R,G, B,CW,WW 5-way dimmer by WIZ dimming signal input
- •Output power can reach 200W, using high frequency PWM control, dimming output smooth
- •LED light without flicker, with the design of eliminating power surge, the LED lamp belt works stably and has a long life span.

Features

- •Manual dimming button/metal shell heat dissipation/multiple temperature protection /flickerless module
- •Signal input buffer design, smooth dimming, timing>=220us
- •Long life span, small size and 35mm DIN-rail installation
- •If the current exceeds 10A or the output is short circuit,

the power supply will automatically lock up and need to be restored by power cut.

•WIZ App remote control, multiple scenario, easy to operate.




Technical Parameters

Model No	LYH-200-24WB5
Brand	LAMMIN
Input Signal	WIZ dimming signal
Signal Type	RGB WW CW
Input Voltage	175V – 240V AC
Input Current Range	1.5A 175V AC 1.1A 240V AC
Rated DC Voltage	24V DC
Frequency Range	50/60Hz
Max Load Current	10A
Max Output	200W
Min Load	200W
Certification	CE
Working Temp	-20℃~+50℃
Warranty	3 years
Size(L*W*H)MM	308*49*31
Installation	35mm DIN rail
Customization	YES

Wiring Diagram and Installations





WIZ APPs

Organize and control your lights by groups within rooms over Wi-Fi or remotely through the cloud. Improve the way you work, feel and simply enjoy the environment you're in with our wide variety of different light modes that cover the range from fun to functional.

